

# LSMX3252LA




ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
in fo@zemper.com
www.zemper.com

## Graphic reference

Datasheet SPAZIO ON



### Dimensions



Control System: DALI2 Luminaire: Self-Contained

**Standards:** EN-60598-1, EN-60598-2-22, EN-62034, EN 61347-2-7, EN 61347-2-13, EN

0598-2-22, EN-62034, EN



Certification: CE, DALI2

### **Electrical characteristics**

**Supply:** 230V 50Hz<0.9W

Maintained mode consumption: - W

Non-maintained mode consumption:  $0.9\ W$ 

Working temperature: 0-40°C Emergency lamp: 1 x LED 3W Emergency lumen output: 250 lm Maintained lumen output: - lm Battery: 3.2V-1.5Ah LFP Class: II Mode: NM Power factor: - %

62386

Signaling Luminaire: -LED temperature: 4000°K

**Duration:** 1 h **Remote control:** Yes **Charging time:** 12 h

## **Mechanical characteristics**

Housing: Polycarbonate

Diffuser: Hall Lens / Wall

Suitable for flammable surfaces: Yes

IP/IK: IP42/IK04

Finish: White RAL9003

Weight: 0,19KG

## ATEX Envelope:

## Photometric curve

## Interdistance

Installation height		
2,0 m	9,12 m	6,89 m
2,5 m	10,13 m	7,95 m
3,0 m	10,99 m	8,86 m
3,5 m	11,70 m	9,72 m



# LSMX3252LA



ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
info@zemper.com
www.zemper.com

## Installation characteristics

SPAZIO ON

Non-maintained luminaires use 4 terminals	(2xL + 2xN)	for supply	/ connection.
---	-------------	------------	---------------

Maintained luminaires use 5 terminals (2xL + 2xN + L1) to enable / disable the maintained mode.

Installation with mounting plate.

Possibility of installation in:

Wall surface.

Possibility of connection with:

Recessed wiring.

Surface tube wiring (max. M20)

Luminaire designed to be installed at high heights (>5m)

		teristics	

Bus available for DALI2 communication.

The luminaire has a status LED, which indicates:

Green LED: OK

Yellow LED flashing: Battery charging or battery connection failure.

LED off: Emergency operation failure or mains failure or defective LED or defective unit.

General Envelope data	



# LSMX3252LA



ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
in fo@zemper.com
www.zemper.com

### **Accessories**

SPAZIO ON



