

LSS3046LAP3




ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
in fo @ ze m p e r . c o m
w w w w . z e m p e r . c o m

Graphic reference

Datasheet SPAZIO SIGN



Dimensions



Control System: DALI2 Luminaire: Self-Contained

Standards: EN-60598-1, EN-60598-2-22, EN-62034, EN 61347-2-7, EN 61347-2-13, EN

61347-2-7, EN 61347-2-13, EN 62386

DALI

Certification: CE, DALI2

Electrical characteristics

Supply: 230V 50Hz<3.6W

 $\label{eq:maintained} \begin{tabular}{ll} \textbf{Maintained mode consumption: } 3.6~W \\ \begin{tabular}{ll} \textbf{Non-maintained mode consumption: } -W \\ \end{tabular}$

Working temperature: 0-40°C Emergency lamp: 8xLEDS 0.5W Emergency lumen output: - Im Maintained lumen output: - Im Battery: 3.2V-1.5Ah LFP Class: II Mode: M

Power factor: - % Signaling Luminaire: -LED temperature: 4000°K

Duration: 3 h **Remote control:** Yes **Charging time:** 12 h

Mechanical characteristics

Envelope: Polycarbonate **Diffuser**: Methacrylate

Suitable for flammable surfaces: Yes

IP/IK: IP42/IK04

Finish: White RAL9003

Weight: 0,68KG

ATEX Envelope:

Photometric curve

Interdistance

Installation height		
2,0 m	-	-
2,5 m	-	-
3,0 m	-	-
3,5 m	-	-



LSS3046LAP3



ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
info@ zemper.com
www.zemper.com

Installation characteristics

SPAZIO SIGN

Maintained luminaires use 3 terminals to enable / disable the maintained mode.

Luminaires made up of a spotlight + electrical equipment with batteries.

Possibility of installation in:

Recessed ceiling.

Ceiling fixing by 2 springs. Vision distance: 25,8 m

Two type of pictograms (according to reference):

Man with arrow up/down : ref LSS***6*** Man with arrow right/left : ref LSS***5***

Operating characteristics

Bus available for DALI2 communication.

The luminaire has a status LED, which indicates:

Green LED: OK

Yellow LED flashing: Battery charging or battery connection failure.

LED off: Emergency operation failure or mains failure or defective LED or defective unit.

General Envelope data		