

## LUZ4300C



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zem per.com w w w.zem per.com

Graphic reference	Dimensions
	100 60   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 100   100 10
Electrical characteristics	
Supply: 230V 50Hz<2.2W	Class: II
Maintained mode consumption: - W Non-maintained mode consumption: 2,2 W	Mode: NM   Power factor: - %
Working temperature: 0-40°C	Signaling Luminaire: -
Emergency lamp: 12xLED 0.5W	LED temperature: 4000°K
Emergency lumen output: 300 lm	Duration: 1 h
Maintained lumen output: - Im	Remote control: No
Battery: 3.6V-1.1Ah Ni-Cd	Charging time: 24 h
Mechanical characteristics	
Housing: Polycarbonate	<b>IP/IK:</b> IP42/IK04
Diffuser: Transparent Polycarbonate	Finish: White RAL9003
Suitable for flammable surfaces: Yes	│ │ Weight: 0,16KG
ATEX Envelope:	
Photometric curve	Interdistance
°00 000 000 000 000 000 000 000 000 000	Installation height $\square \longleftrightarrow \square$ $\square \Leftrightarrow \square$ 2,0 m9,03 m9,01 m2,5 m9,98 m9,97 m3,0 m10,79 m10,79 m
30°	3,5 m 11,49 m 11,48 m
160	



LUZ4300C



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

## Installation characteristics

Non-maintained luminaires use 4 terminals (2xL + 2xN) for supply connection. Maintained luminaires use 5 terminals (2xL + 2xN + L1) to enable / disable the maintained mode. Installation with mounting plate. Possibility of installation in: Ceiling/Wall surface. Recessed ceiling (with installation accessory) Possibility of connection with: Recessed wiring. Surface tube wiring (max. M20)

**Operating characteristics** 

The luminaire has a status LED, which indicates: Status of the battery charging circuit. Green on = Battery charge OK. Off = Wrong battery charge. Remote control input that allows: Put on standby without power supply.

## General Envelope data



LUZ4300C



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

## Accessories













