

# LKS3070LXP3




ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
in fo@zemper.com
www.zemper.com

#### Graphic reference

**KONS** 



#### Dimensions



Control System: AutoTest Luminaire: Self-Contained

**Standards:** EN-60598-1, EN-60598-2-22, EN-62034

Certification: CE, KITEMARK, CIVIL DEFENSE



#### **Electrical characteristics**

Supply: 230V 50Hz<3.6W

 $\label{eq:maintained} \begin{tabular}{ll} \textbf{Maintained mode consumption: } 3.6~W \\ \begin{tabular}{ll} \textbf{Non-maintained mode consumption: } -W \\ \end{tabular}$ 

Working temperature: 0-40°C Emergency lamp: 8xLEDS 0.5W Emergency lumen output: - Im Maintained lumen output: - Im Battery: 3.2V-1.5Ah LFP Class: II Mode: M

Power factor: - % Signaling Luminaire: -LED temperature: 4000°K

Duration: 3 h
Remote control: Yes
Charging time: 12 h

#### **Mechanical characteristics**

**Envelope**: Polycarbonate **Diffuser**: Methacrylate

Suitable for flammable surfaces: Yes

IP/IK: IP42/IK04

Finish: White RAL9003

Weight: 0,98KG

ATEX Envelope:

## Photometric curve

### Interdistance

Installation height		
2,0 m	-	-
2,5 m	-	-
3,0 m	-	-
3,5 m	_	_



# Datasheet LKS3070LXP3



ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
in fo@zemper.com

#### Installation characteristics

**KONS** 

Installation with mounting plate. Possibility of installation in:

Ceiling surface. Wall mural.

Wall flag.

Possibility of connection with:

Surface tube wiring.

Vision distance: 25,8 m

#### Operating characteristics

The luminaire has status LEDs, which indicates:

Status of the battery charging circuit.

Battery status (duration)

Emergency status function.

Test status.

Microprocessor controlled luminaire that performs periodic and automatic tests.

Functional test every 7 days.

Duration test every 365 days.

The test result is shown in the status indicator LEDs.

Remote control input that allows:

Put on Standby without power supply.

Restart in emergency status without power supply.

Switch on in emergency status (more than 24 h of charge)

Manual and remote duration test. (more than 24 hours of charge).

Date and time programming of the tests.

Reset of the luminaire status.

General Envelope data		