

Datasheet SPAZIO NANO

LML9251LX




ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
info@zemper.com

Graphic reference



Dimensions



Control System: AutoTest

Luminaire: Self-Contained

Standards: EN-60598-1, EN-60598-2-22, EN-62034

Certification: CE, ENEC



Electrical characteristics

Supply: 230V 50Hz<1.0W

Maintained mode consumption: - W

Non-maintained mode consumption: 1,0 $\,\mathrm{W}$

Working temperature: 0-40°C Emergency lamp: 1XLEDS 3W Emergency lumen output: 280 lm Maintained lumen output: - lm Battery: 3.2V-1.5Ah LFP Class: II Mode: NM

Power factor: - %

Signaling Luminaire: -

LED temperature: 4000°K

Duration: 1 h Remote control: Yes Charging time: 12 h

Mechanical characteristics

Housing: Polycarbonate **Diffuser:** Escape Lens

Suitable for flammable surfaces: Yes

IP/IK: IP42/IK04

Finish: White RAL9003

Weight: 0,20KG

ATEX Envelope:

Photometric curve

90° 60° 30° 160

Interdistance

Installation height		
2,0 m	7,38 m	23,89 m
2,5 m	7,87 m	26,57 m
3,0 m	8,21 m	28,45 m
3,5 m	8,43 m	30,15 m



LML9251LX



ELECTROZEMPER S.A.
Avda. de la Ciencia s/n.
Parque Ind. Avanzado
13005 Ciudad Real. Spain.
Tel.: +34 902 11 11 97
Fax: +34 902 11 11 97
in fo@zemper.com

Installation characteristics

SPAZIO NANO

Maintained luminaires use 3 mains supply inputs (L, L1, N) to enable / disable the maintained mode
Luminaires made up of a spotlight + electrical equipment with batteries (Self-contained luminaires).
Possibility of installation in:

On suspended ceiling.

Recessed ceiling (Slat ceilings) with accessory (incluided).

Continuous rail.

Operating characteristics

The luminaire has status LEDs, which indicates:

Status of the battery charging circuit.

Battery status (duration)

Emergency status function.

Test status.

Microprocessor controlled luminaire that performs periodic and automatic tests.

Functional test every 7 days.

Duration test every 365 days.

The test result is shown in the status indicator LEDs.

Remote control input that allows:

Put on Standby without power supply.

Restart in emergency status without power supply.

Switch on in emergency status (more than 24 h of charge)

Manual and remote duration test. (more than 24 hours of charge).

Date and time programming of the tests.

Reset of the luminaire status.

G	General Envelope data		