


LSMX3101LW3



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

Graphic reference






Electrical characteristics

Mechanical characteristics

Supply: 230V 50Hz<0.9W	Class: II	
Maintained mode consumption: - W	Mode: NM	
Non-maintained mode consumption: 0,9 W	Power factor: - %	
Working temperature: 0-40°C	Signaling Luminaire: -	
Emergency lamp: 1 x LED 3W	LED temperature: 4000°K	
Emergency lumen output: 95 lm	Duration: 3 h	
Maintained lumen output: - Im	Remote control: No	
Battery: 3.2V-1.8Ah LFP	Charging time: 12 h	

Housing: Polycarbonate IP/IK: IP42/IK04 Diffuser: Escape Lens Finish: White RAL9003 Suitable for flammable surfaces: Yes Weight: 0,19KG ATEX Envelope: Image: Suitable for flammable surfaces in the surface surface

Photometric curve



Interdistance

Installation height		
2,0 m	16,06 m	5,45 m
2,5 m	18,52 m	6,27 m
3,0 m	20,82 m	6,85 m
3,5 m	22,91 m	7,16 m



LSMX3101LW3



 $\begin{array}{l} \mathsf{ELECTROZEMPER} \quad S.A.\\ \mathsf{Avda} \quad de \quad la \quad \mathsf{Ciencia} \quad \mathsf{s/n}.\\ \mathsf{Parque} \quad \mathsf{Ind} \quad \mathsf{Avaraado}\\ \mathsf{13005} \quad \mathsf{Ciudad} \quad \mathsf{Real}. \quad \mathsf{Spain}.\\ \mathsf{rbl:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{11} \quad \mathsf{11} \quad \mathsf{97}\\ \mathsf{rax:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{11} \quad \mathsf{11} \quad \mathsf{97}\\ \mathsf{rax:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{11} \quad \mathsf{11} \quad \mathsf{97}\\ \mathsf{rax:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad$

Installation characteristics

Non-maintained luminaires use 4 terminals (2xL + 2xN) for supply connection. Maintained luminaires use 5 terminals (2xL + 2xN + L1) to enable / disable the maintained mode. Installation with mounting plate. Possibility of installation in: Ceiling surface. Recessed ceiling (with installation accessory) Possibility of connection with: Recessed wiring. Surface tube wiring (max. M20) Luminaire for corridor lighting.

Operating characteristics

The luminaire has status LEDs, which indicates:
Status of the battery charging circuit.
Battery status (duration)
Emergency status function.
Test status.
Microprocessor controlled luminaire
The luminaire can be connected to a control unit.
When the luminaire is installed without a control unit, it performs periodic and automatic tests.
Functional test every 7 days.
Duration test every 365 days.
The test result is shown in the status indicator LEDs.
Wireless communication that allows: Communication with Control unit by wireless communication with a 2.4Ghz frequency system.

General Envelope data



LSMX3101LW3



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

Accessories





CEILING ROUND





