

LSP3175LAP3



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zem per.com w w w.zem per.com

Graphic reference	Dimensions
	Control System: DALI2 Luminaire: Self-Contained
	Standards: EN-60598-1, EN-60598-2-22, EN-62034, EN Certification: CE, DALI2, ENEC, CIVIL DEFENSE 61347-2-7, EN 61347-2-13, EN ENEC, CIVIL DEFENSE 62386 ENEC
Electrical characteristics	
Supply: 230V 50Hz<2.5W	Class:
Maintained mode consumption: 2,5 W	Mode: M/NM
Non-maintained mode consumption: 0,9 W	Power factor: - %
Working temperature: 0-40°C	Signaling Luminaire: -
Emergency lamp: 1 x LED 3W	LED temperature: 4000°K
Emergency lumen output: 165 lm	Duration: 3 h
Maintained lumen output: 100 lm	Remote control: Yes
Battery: 3.2V-1.8Ah LFP	Charging time: 12 h
Mechanical characteristics	
Housing: Polycarbonate	IP/IK: IP42/IK04
Diffuser: Circular Lens + Hall	Finish: White RAL9003
Suitable for flammable surfaces: Yes	Weight: 0,19KG
ATEX Envelope:	
Photometric curve	Interdistance
	Installation height $7,41 \text{ m}$ $7,41 \text{ m}$
90°	
20	2,5 m 8,47 m 8,47 m
60°	3,0 m 9,43 m 9,43 m
	3,5 m 10,25 m 10,25 m
30° / [100 2 - 30°	



LSP3175LAP3



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

Installation characteristics

Non-maintained luminaires use 4 terminals (2xL + 2xN) for supply connection. Maintained luminaires use 5 terminals (2xL + 2xN + L1) to enable / disable the maintained mode. Installation with mounting plate. Possibility of installation in: Ceiling/Wall surface. Recessed ceiling (with installation accessory) Possibility of connection with: Recessed wiring. Surface tube wiring (max. M20)

Operating characteristics

Bus available for DALI2 communication.

The luminaire has a status LED, which indicates:

Green LED: OK

Yellow LED flashing: Battery charging or battery connection failure.

LED off: Emergency operation failure or mains failure or defective LED or defective unit.

General Envelope data



LSP3175LAP3



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

Accessories













