


LST3502LXP



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zem per.com w w w.zem per.com

| Graphic reference | Dimensions | |
|--|--|--|
| | 220 90 90 91 920 91 920 </th | |
| Electrical characteristics | | |
| Supply: 230V 50Hz<3.8W | Class: II | |
| Maintained mode consumption: 3,8 W | Mode: M/NM | |
| Non-maintained mode consumption: 1,0 W | Power factor: - % | |
| Working temperature: 0-40°C | Signaling Luminaire: - | |
| Emergency lamp: 2XLEDS 3W | LED temperature: 4000°K | |
| Emergency lumen output: 500 lm | Duration: 1 h | |
| Maintained lumen output: 300 lm | Remote control: Yes | |
| Battery: 3.2V-3.0Ah LFP | Charging time: 12 h | |
| Mechanical characteristics | | |
| | | |
| Housing: Polycarbonate | IP/IK: IP42/IK04 | |
| Diffuser: Hall Lens / Wall | Finish: White RAL9003 | |
| Suitable for flammable surfaces: Yes | Weight: 0,53KG | |
| ATEX Envelope: | | |

Photometric curve



Interdistance

| Installation height | | |
|------------------------|---------|---------|
| 2,0 m | 10,32 m | 8,09 m |
| 2,5 m | 11,54 m | 9,26 m |
| 3,0 m | 12,55 m | 10,29 m |
| 3,5 m | 13,53 m | 11,37 m |



LST3502LXP



 $\begin{array}{l} \mathsf{ELECTROZEMPER} \quad S.A.\\ \mathsf{Avda} \quad de \quad la \quad \mathsf{Ciencia} \quad \mathsf{s/n}.\\ \mathsf{Parque} \quad \mathsf{Ind} \quad \mathsf{Avaraado}\\ \mathsf{13005} \quad \mathsf{Ciudad} \quad \mathsf{Real}. \quad \mathsf{Spain}.\\ \mathsf{rbl:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{11} \quad \mathsf{11} \quad \mathsf{97}\\ \mathsf{rax:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{11} \quad \mathsf{11} \quad \mathsf{97}\\ \mathsf{rax:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{11} \quad \mathsf{11} \quad \mathsf{97}\\ \mathsf{rax:} \quad \mathsf{r34} \quad \mathsf{902} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{r3m} \quad \mathsf{rax:} \quad \mathsf{r3m} \quad \mathsf{r3m}$

Installation characteristics

The permanent luminaires have three network connection terminals to enable / disable the permanent function. Installation with preplate. Possibility of installation: Wall surface (special lighting for corridors and landings) Possibility of connection: Embedded wiring

Operating characteristics

The luminaire has status LEDs, which indicates:
Status of the battery charging circuit.
Battery status (duration)
Emergency status function.
Test status.
Microprocessor controlled luminaire that performs periodic and automatic tests.
Functional test every 7 days.
Duration test every 365 days.
The test result is shown in the status indicator LEDs.

Remote control input that allows:

Put on Standby without power supply. Restart in emergency status without power supply. Switch on in emergency status (more than 24 h of charge) Manual and remote duration test. (more than 24 hours of charge). Date and time programming of the tests. Reset of the luminaire status.

General Envelope data



LST3502LXP



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zemper.com w w w.zemper.com

Accessories

