

LYA3600LX



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zemper.com w w w.zemper.com

Graphic reference	Dimensions
A second se	155 100 1
Electrical characteristics	
Supply: 230V 50Hz<2.2W Maintained mode consumption: - W Non-maintained mode consumption: 2.2 W Working temperature: 0-40°C Emergency lamp: 6xLED 0.5W Emergency lumen output: 600 lm Maintained lumen output: - Im Battery: 6.4V-1.5Ah LFP	Class: II Mode: NM Power factor: - % Signaling Luminaire: - LED temperature: 4000°K Duration: 1 h Remote control: No Charging time: 24 h
Mechanical characteristics	
Envelope: Polycarbonate Diffuser: Ambient + Directional Lens Suitable for flammable surfaces: Yes	IP/IK: IP42/IK04 Finish: White RAL9003 Weight: 0,16KG
ATEX Envelope:	
Photometric curve	Interdistance
105° 90° 75° 60° 45° 240 45° 240 45° 240 45° 45° 45° 45° 45° 45° 45° 45°	Installation height □ ← → □ □ ← → □ 2,0 m 11,87 m 7,58 m 2,5 m 14,84 m 9,48 m 3,0 m 17,81 m 11,37 m 3,5 m 20,78 m 13,27 m



LYA3600LX



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel:: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo@zemper.com www.zemper.com

Installation characteristics

Maintained luminaires use 4 terminals (2xL + 2xN). Luminaires have a selector bridge to enable / disable the maintained mode. Installation with mounting plate. Possibility of installation in: Ceiling/Wall surface. Recessed ceiling (with installation accessory) Possibility of connection with: Recessed wiring.

Operating characteristics

The luminaire has status LEDs, which indicates: Status of the battery charging circuit. Battery status (duration) Emergency status function. Test status. Microprocessor controlled luminaire that performs periodic and automatic tests. Functional test every 7 days. Duration test every 365 days. The test result is shown in the status indicator LEDs.

Remote control input that allows:

Put on Standby without power supply. Restart in emergency status without power supply. Switch on in emergency status (more than 24 h of charge) Manual and remote duration test. (more than 24 hours of charge). Date and time programming of the tests. Reset of the luminaire status.

General Envelope data



LYA3600LX



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zemper.com w w w.zemper.com

Accessories

