


# LYAX5400LA



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zem per.com w w w.zem per.com

Graphic reference	Dimensions		
	Image: Control System: DALI2 Luminaire: Self-Contained   Standards: EN-60598-1, EN-60598-2-22, EN-62034, EN 61347-2-7, EN 61347-2-13, EN 62386 Certification: CE, DALI2		
Electrical characteristics	62386 <b>DALI</b>		
Supply: 230V 50Hz<0.9W	Class: II		
Maintained mode consumption: - W	Mode: NM		
Non-maintained mode consumption: 0,9 W	Power factor: - %		
Working temperature: 0-40°C	Signaling Luminaire: -		
Emergency lamp: 6xLED 0.5W	LED temperature: 4000°K		
Emergency lumen output: 390 lm	Duration: 1 h		
Maintained lumen output: - Im	Remote control: Yes		
Battery: 3.2V-1.5Ah LFP	Charging time: 12 h		
Mechanical characteristics			
Housing: Polycarbonate	IP/IK: IP42/IK04		
Diffuser: Ambient + Directional Lens	Finish: White RAL9003		
Suitable for flammable surfaces: Yes			
	Weight: 0,16KG		
ATEX Envelope:			
Photometric curve	Interdistance		
105* 105* 90* 90*	Installation		



Installation height		
2,0 m	7,58 m	11,87 m
2,5 m	9,48 m	14,84 m
3,0 m	11,36 m	17,81 m
3,5 m	12,20 m	18,88 m



## LYAX5400LA



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ z em per.com w w w.z em per.com

### Installation characteristics

Maintained luminaires use 4 terminals (2xL + 2xN). Luminaires have a selector bridge to enable / disable the maintained mode. Installation with mounting plate. Possibility of installation in: Ceiling/Wall surface. Recessed ceiling (with installation accessory) Possibility of connection with: Recessed wiring.

#### **Operating characteristics**

Bus available for DALI2 communication.

The luminaire has a status LED, which indicates:

Green LED: OK

Yellow LED flashing: Battery charging or battery connection failure.

LED off: Emergency operation failure or mains failure or defective LED or defective unit.

### General Envelope data



# LYAX5400LA



ELECTROZEMPER S.A. Avda. de la Ciencia s/n. Parque Ind. Avanzado 13005 Ciudad Real. Spain. Tel.: +34 902 11 11 97 Fax: +34 902 11 11 97 in fo @ zemper.com w w w.zemper.com

Accessories

